

COAXIAL ADAPTER SET

The TBCAS1 coaxial adapter set contains 44 pieces of the most common 50 Ohm coaxial adapters in a beech wood box.



COAXIAL ADAPTER SET

1 Parts list

Pieces	Type	Frequency	VSWR	Pieces	Type	Frequency	VSWR
1	N-male to N-male	6 GHz	1.1 - 1.15	1	BNC-female to BNC-female	4 GHz	1.2
1	N-female to N-female	6 GHz	1.1 - 1.15	1	BNC-male to RCA-female	100 MHz	1.2
4	N-male to SMA-female	6 GHz	1.1 - 1.15	1	BNC-female to RCA-male	100 MHz	1.2
2	N-male to SMA-male	6 GHz	1.1 - 1.15	1	BNC-male to SMA-male	4 GHz	1.2
2	N-male to SMB-female	6 GHz	1.1 - 1.15	2	BNC-male to SMA-female	4 GHz	1.2
4	N-male to BNC-female	4 GHz	1.2	1	BNC-female to SMA-male	4 GHz	1.2
1	N-male to BNC-male	4 GHz	1.2	2	BNC-female to SMA-female	4 GHz	1.2
1	N-female to BNC-male	4 GHz	1.2	3	SMA-female to SMA-female	6 GHz	1.1 - 1.15
1	N-female to BNC-female	4 GHz	1.2	3	SMA-male to SMA-male	6 GHz	1.1 - 1.15
2	N-female to SMA-female	6 GHz	1.1 - 1.15	2	SMA-male to SMB-male	6 GHz	1.1 - 1.15
2	N-female to SMA-male	6 GHz	1.1 - 1.15	2	SMA-male to SMB-female	6 GHz	1.1 - 1.15
1	N-female to SMB-female	6 GHz	1.1 - 1.15	2	SMA-male to SMB-male	6 GHz	1.1 - 1.15
1	BNC-male to BNC-male	4 GHz	1.2				

Dimensions: 190mm x 170mm x 65mm
Weight: 1.3 kg

2 Ordering Information

Part Number	Description
TBCAS1	44pcs coaxial adapter set, beech-wood box